AK10 Firmware V1.10 Upgrade Guide

[Improvement]

1. Support up to 24bit/96kHz when specific applications are used on Apple devices. (e.g. Flac player (non free App.), Onkyo HF player))

Note: Pre-installed music player on Apple devices supports up to 24bit/48kHz only.

- 1. Download the attached firmware tool file.
- 2. Decompress the file then you can see 4 files.
- 3. Power off the AK10 (Slide the power key to the left for 3 sec.) and check LED off.
- 4. Connect the AK10 to PC by USB cable with the RW & FF keys pressed together.
- 5. Then, LED color gets purple. (Blue + Red lights)
- 6. Execute 'AK10_FirmwareTool.exe' that was downloaded at step #2 and check the device is Connected as below.

AK10 Firmware upgrade Tool	
AK10 Connection: Connected Status Log	Start
Directory Opened - C:\AK10_FW_v1,10 firmware file found - [AK10,cyacd]	~

- 7. Click 'Start' key on the right.
- 8. Check the upgrade status on the window.
- 9. After it's completed, the AK10 is automatically disconnected and LED light turns off.
- 10. Disconnect the AK10 from PC, then it's automatically powered on.